



Model:YD-606





## **Basic Instruction**

Dual Voltage Selectable (12VDC or 24VDC) **Emergency Release Button/Test Button** Wall Mounting Direction

Low Current Consumption Reliable Fail-Safe Mechanism **Durable and Silence Operation** 

## **Specifications**

Size: 80Lx80Wx120H(mm)

Voltage: 12/24VDC+10%(Adjustment)

Current Draw: 12V/140mA 24V/70mA

• Optional: Manual door release button

• Surface Temp: ≤+20°C

Operating Temp: 0~+55℃(14-131F)

• Weight: 1.05kg

Holding Force: 50kg(110Lbs)

• Suitable for: All Kinds of Single (Double) Smokeproof Doors


• Suitable Humidity: 0~95%


• Finishes for Shell: High Temperature Paint Environmental

**Protection Zinc** 

• Finishes for Armature: Chromium

#### **Dimension**





## Installation

# Remarks:

- 1. The default setting is 24VDC.
- 2. If user want to connect with 12VDC, operating as below:
- (1) Pull those two jumpers out. It is showed 4 pins here.
- (2) To set up 12VDC, insert one jumper on the position of 1 and 2, second jumper on the position of 3 and 4.

